

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://mersen.nt-rt.ru/> || mnh@nt-rt.ru

UL 508 Non-Fusible

Disconnect Switches

DISCONNECT SWITCHES

M163 – M803



The M-series Load Break Switch is the most compact industrial-grade switch on the market. Capable of making or breaking loads up to 600V (UL), it is suitable as a motor disconnect. Extremely compact and robust, these switches have a variety of mounting options including DIN-rail, base, or door-mounting. A wide assortment of handles, shafts and accessories is available to accommodate any installation requirement.

APPLICATIONS:

- Line-of-sight disconnect
- Electrical isolation
- Branch-circuit switch
- Motor disconnect

RATINGS (UL):

- **Volts:** 600VAC
- **Amps:** 20, 30, 40, 63, and 80A. Suitable as motor disconnect up to 40hp.

FEATURES/ BENEFITS:

- Compact
- Robust
- DIN-rail, base, or door mounting
- Choice of handles and shafts
- Padlockable
- Side-mount auxiliary contacts and additional poles
- Double-break, silver-plated, contacts

APPROVALS:

- UL 508 listed E196672
- IEC 60947-3






DS

Catalog number designation			
M Switch	80 Ampacity	3 Number of Poles	Special Configurations
M = Mersen AC Switch	16-80		DM: Door Mounting



UL 508 NON-FUSIBLE Disconnect Switches (M163 - M803)

UL 508 Disconnect Switches—Front Operated

 <p>M163</p>	 <p>M163DM</p>	 <p>M633</p>	 <p>M633DM</p>							
Switch Body	Ampere Rating					20	30	40	63	80
	Base Part #	M163	M253	M403	M633	M803				
	Door-Mounted Version	M163DM	M253DM	M403DM	M633DM	M803DM				
Handles and Shafts	Direct Front Operation Locking Handle									
 <p>HD40</p> <p>HB65</p> <p>SA105</p> <p>SPA130</p>						HD40	HD40	HD40	HD125	HD125
	External Front Operation									
	Selector Style NEMA Type 1, 3R, 12	HSBX, HSRX								
	Shaft—SAxxx (xxx = length in mm)	SA85, SA105, SA120, SA130, SA180, SA250								
	Door mounted version (no shaft required)	HSBPDM, HSRPDM				HSBWDM, HSRWDM				
	Pistol Style NEMA Type 1, 3R, 12	HB45, HR45, HB65, HR65, HB80, HR80								
	NEMA Type 4, 4X	HB45X, HR45X, HB65X, HR65X, HB80X, HR80X								
	NEMA 4X Stainless Steel	HM65X								
	Shaft— SAxxx (xxx = length in mm)	SPA130, SPA210, SPA290, SPA360, SPA430								
	B=Black, R=Black									
Accessories	Fourth Poles									
	Limited to one additional pole per switch	4P40	4P40	4P40	4P80	4P80				
	Door mounted switch 4th poles are left-side mounted	4P40DM	4P40DM	4P40DM	4P80DM	4P80DM				
	Neutral Poles									
	Limited to one additional pole per switch	NP40	NP40	NP40	NP80	NP80				
	Door mounted switch neutral poles	NP40DM	NP40DM	NP40DM	NP80DM	NP80DM				
	Terminal Shrouds									
	3-pole	TS40-3	TS40-3	TS40-3	TS63-3	TS63-3				
	4-pole (Add this to the 3-pole shroud)	TS40-1	TS40-1	TS40-1	TS63-1	TS63-1				
	Auxiliary Contacts*									
	NC Right side mounting	OA1G01	OA1G01	OA1G01	OA1G01	OA1G01				
	NO left side mounting	OA1G10	OA1G10	OA1G10	OA1G10	OA1G10				
	NO+NC (Mounting on either side)	OA2G11	OA2G11	OA2G11	OA2G11	OA2G11				
	*Rated 2A max continuous @690VAC									
Minimum switching capacity for the auxiliary contacts OA1G01, OA1G10, OA2G11 is 10mA at a voltage of 24V DC										

UL 508 NON-FUSIBLE Disconnect Switches (M163 - M803)

LOW VOLTAGE
DISCONNECT SWITCHES

TECHNICAL DATA ACCORDING TO UL/cULus													
Part Number				M163		M253		M403		M633		M803	
General Purpose Amp Rating	pf= 0.7...0.8	-40° to 40 °C	A	20	30	40	60	80					
Maximum Operating Voltage			V	600	600	600	600	600					
Max. horsepower rating / motor FLA current	pf= 0.4...0.5 Three phase	240 V	HP/A	5/15.2	7.5/22.0	10/28.0	15/42.0	20/54.0					
		480 V	HP/A	10/14.0	15/21.0	20/27.0	30/40.0	40/52.0					
		600 V	HP/A	11-Oct	20/22.0	25/27.0	30/32.0	40/41.0					
	Single phase	120 V	HP/A	1/16.0	1.5/20.0	2/24.0	2/24.0	2/24.0					
		240 V	HP/A	2/13.2	3/18.7	5/30.8	7.5/40.0	10/57.5					
Short circuit rating with fuse	Maximum fuse size		A	30	60 ²⁾	30	60 ²⁾	30	60 ²⁾	100	150	100	150
	Fuse type	CC	kA	10		10		10					
	Fuse type	J	kA	10	10	10	10	10	100			100	
	Fuse type	T	kA	10	10	10	10	10	100			100	
	Fuse type	RK1	kA	10		10		10		10	5	10	5
	Fuse type	RK5	kA	5	5	5	5	5		5			5
	Fuse type	L	kA										
	Fuse type	H	kA										
Endurances													
Min. electrical endurance, pf. 0.75...0.8			oper. cycles	6 000	6 000	6 000	6 000	6 000					
Mechanical endurance			operations	20 000	20 000	20 000	20 000	20 000					
Terminal lug kits				Integral	Integral	Integral	Integral	Integral					
Wire range			AWG	18-8	18-8	18-8	14-4	14-4					
Torque		Wire tightening	lb. in	7	7	7	18	18					
		Lug mounting											

TECHNICAL DATA ACCORDING TO UL/cULus									
Part Number	General Purpose Amp Rating			M163	M253	M403	M633	M803	
	pf= 0.7...0.8	-40° to 40 °C	A	20	30	40	60	80	
TECHNICAL DATA ACCORDING TO IEC 60947-3									
Rated insulation voltage and rated operational voltage AC20/DC20	Pollution degree 3	50 Hz 1 min.	V	750	750	750	750	750	
Dielectric strength			kV	6	6	6	6	6	
Rated impulse withstand voltage			kV	8	8	8	8	8	
Rated thermal current and rated operational current AC20/DC20	Ambient 40 °C ²⁾	In open air		25 A	32 A	40 A	63 A	80 A	
	Ambient 40 °C ²⁾	In enclosure		25 A	32 A	40 A	63 A	80 A	
	Ambient 60 °C	In enclosure		20 A	25 A	32 A	50 A	63 A	
...with minimum conductor cross		Cu		4 mm ²	6 mm ²	10 mm ²	16 mm ²	25 mm ²	
Rated operational current, AC-21A		up to 415 V	A	16	25	40	63	80	
		440...690 V	A	16	25	40	63	80	
Rated operational current, AC-22A		up to 415 V	A	16	25	40	63	80	
		440...690 V	A	16	25	40	63	80	
Rated operational current, AC-23A		up to 415 V	A	16	20	23	63	75	
		440 V	A	16	20	23	63	65	
		500 V	A	16	20	23	45	58	
		690 V	A	10	11	12	20	20	
Rated operational current / poles in series, DC-21A		24...48 V ¹⁾		16 A/1	25 A/1	32 A/1	63 A/1	80 A/1	
		110 V		16 A/2	25 A/2	32 A/2	63 A/2	80 A/2	
		220 V		16 A/3	25 A/3	32 A/3	63 A/3	80 A/3	
		440 V		16 A/4	16 A/4	16 A/4	16 A/4	16 A/4	
		500 V		16 A/4	16 A/4	16 A/4	16 A/4	16 A/4	
		750 V		16 A/8	25 A/8	32 A/8	-	-	
Rated operational current / poles in series, DC-22A		24...48 V ¹⁾		16 A/1	25 A/1	32 A/1	63 A/1	80 A/1	
		110 V		16 A/2	25 A/2	32 A/2	63 A/2	80 A/2	
		220 V		16 A/3	25 A/3	32 A/4	45 A/4	45 A/4	
		440 V		10 A/4	10 A/4	10 A/4	10 A/4	10 A/4	
		750 V		16 A/8	25 A/8	25 A/8	-	-	
		24...48 V ¹⁾		16 A/1	25 A/1	32 A/1	63 A/1	80 A/1	
Rated operational current / poles in series, DC-23A		110 V		16 A/2	25 A/2	32 A/2	63 A/2	80 A/2	
		220 V		16 A/4	25 A/3	32 A/4	45 A/4	45 A/4	
		440 V		10 A/4	10 A/4	10 A/4	10 A/4	10 A/4	
		750 V		16 A/8	16 A/8	16 A/8	-	-	
		220...240 V		3 kW	4 kW	5.5 kW	11 kW	22 kW	
		400...415 V		7.5 kW	9 kW	11 kW	22 kW	37 kW	
Rated operational power, AC-23A (These values are given for guidance and may vary acc. to the motor manufacturer)		440...500 V		7.5 kW	9 kW	11 kW	22 kW	37 kW	
		690 V		7.5 kW	9 kW	11 kW	15 kW	18.5 kW	
	Rated breaking capacity, AC-23A		up to 415 V		128 A	160 A	184 A	360 A	640 A
			440 V		128 A	160 A	184 A	360 A	448 A
		500 V		128 A	160 A	184 A	360 A	464 A	
		690 V		80 A	88 A	96 A	160 A	160 A	
		24...48 V		64 A/1	100 A/1	128 A/1	180 A/1	252 A/1	
Rated breaking capacity/ poles in series, DC-23A		110 V		64 A/2	100 A/2	128 A/2	180 A/2	252 A/2	
		220V		64 A/3	100 A/4	128 A/4	180 A/4	180 A/4	
		440 V		40 A/4	40 A/4	40 A/4	40 A/4	40 A/4	
		750 V		64 A/8	64 A/8	64 A/8	-	-	
	Rated conditional short-circuit current I _a (r.m.s.) and corresponding max. Allowed cut-off current I _c of fuse. The cut-off current I _c refers to values listed by fuse manufacturers (single phase test acc. To IEC60269)	I _a 50kA, ≤415V Max. OFA fuse size	I _c		6.5 kA	6.5 kA	6.5 kA	13 kA	13 kA
I _a 100kA, 500V Max. OFA fuse size		I _c		-	-	-	17 kA	17 kA	
I _a 10kA, 690V Max. OFA fuse size		I _c		-	-	-	-	-	
I _a 50kA, 690V Max. OFA fuse size		I _c		4 kA	4 kA	4 kA	11 kA	11 kA	
Rated short-time withstand current	r.m.s.-value I _{cw}	690 V, 1 s	kA	0.5	0.5	0.5	1	1.5	
Rated short circuit making capacity	Peak value I _{cm}	690 V/500 V	A	0.71	0.71	0.71	1.4	2.1	
Rated capacitor power [the capacitor ratings are limited by the fuse link.]		400...415 V		6.5 kVAr	10 kVAr	15 kVAr	25 kVAr	30 kVAr	
Power loss / pole	At rated operational current		W	0.3	0.6	1.6	2.8	4.5	
Mechanical endurance	Divide by two for operation cycles		Oper.	20 000	20 000	20 000	20 000	20 000	
Weight without accessories		3-pole	kg	0.11	0.11	0.11	0.27	0.27	
		4-pole	kg	0.15	0.15	0.15	0.35	0.35	
Cable size	Cu-wire size suitable for terminal clamps			0.75...10 mm ²	0.75...10 mm ²	0.75...10 mm ²	1.5...35 mm ²	1.5...35 mm ²	
				18-8 AWG	18-8 AWG	18-8 AWG	14-4 AWG	14-4 AWG	
Terminal tightening torque	Counter torque required			0.8 Nm	0.8 Nm	0.8 Nm	2 Nm	2 Nm	
Operating torque	3-pole switch-disconnector			1 Nm	1 Nm	1 Nm	1.2 Nm	1.2 Nm	

1) UL Listed switches are also CSA Approved. 2) Fuse size 70A for RK5.

Below 48 V, two poles in parallel up to M803 are recommended particularly in polluted atmosphere.

Архангельск (8182)63-90-72	Ижевск (3412)26-03-58	Магнитогорск (3519)55-03-13	Пермь (342)205-81-47	Сургут (3462)77-98-35
Астана (7172)727-132	Иркутск (395)279-98-46	Москва (495)268-04-70	Ростов-на-Дону (863)308-18-15	Тверь (4822)63-31-35
Астрахань (8512)99-46-04	Казань (843)206-01-48	Мурманск (8152)59-64-93	Рязань (4912)46-61-64	Томск (3822)98-41-53
Барнаул (3852)73-04-60	Калининград (4012)72-03-81	Набережные Челны (8552)20-53-41	Самара (846)206-03-16	Тула (4872)74-02-29
Белгород (4722)40-23-64	Калуга (4842)92-23-67	Нижний Новгород (831)429-08-12	Санкт-Петербург (812)309-46-40	Тюмень (3452)66-21-18
Брянск (4832)59-03-52	Кемерово (3842)65-04-62	Новокузнецк (3843)20-46-81	Саратов (845)249-38-78	Ульяновск (8422)24-23-59
Владивосток (423)249-28-31	Киров (8332)68-02-04	Новосибирск (383)227-86-73	Севастополь (8692)22-31-93	Уфа (347)229-48-12
Волгоград (844)278-03-48	Краснодар (861)203-40-90	Омск (3812)21-46-40	Симферополь (3652)67-13-56	Хабаровск (4212)92-98-04
Вологда (8172)26-41-59	Красноярск (391)204-63-61	Орел (4862)44-53-42	Смоленск (4812)29-41-54	Челябинск (351)202-03-61
Воронеж (473)204-51-73	Курск (4712)77-13-04	Оренбург (3532)37-68-04	Сочи (862)225-72-31	Череповец (8202)49-02-64
Екатеринбург (343)384-55-89	Липецк (4742)52-20-81	Пенза (8412)22-31-16	Ставрополь (8652)20-65-13	Ярославль (8852)69-52-93
Иваново (4932)77-34-06				

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31